

CIOKS AC10 Power Supply

AC10

Power Supply

AC10 is a member of CIOKS professional range of dedicated multi-output power supplies for effect pedals. Its two powerful AC sections with 800mA each offer voltages 9, 12 and 16V AC. If you have one or two pedals in your setup, which requires an AC power source, AC10 is the right choice. It powers all vacuum tube pedals from Electro-Harmonix, Kingsley, older Blackstar HT series, the Whammy or JamMan from DigiTech, Tube Rotosphere, Tubeman, Tube Factor or Replex from Hughes & Kettner or EBS Valve Drive just to mention a few. If you only have one AC pedal, you can convert one of the AC sections into a powerful DC section offering 600mA with voltages 9, 12 and 15V DC. The first 4 isolated outlets offering a total of 600mA are ideal for pedals using 9 or 12V DC at lower currents up to 200mA.

Features:

- 10 outlets configured in 6 isolated sections
- toroidal transformer with additional magnetic field shielding
- 2 powerful AC sections with 800mA each
- 9, 12 and 16V AC available
- one AC section convertible into a 600mA DC section
- 15V option for Radial Tonebone pedals
- short circuit protection of all outlets
- advanced LED monitoring of each section
- temperature monitoring
- 120 or 230V mains voltage operation
- detachable mains power cord
- a total of 17 Flex cables included
- Flex cable for Electro-Harmonix vacuum tube pedals from included
- one Split Flex and one Stack Flex for 18V pedals also included
- mounting bracket included
- durable steel enclosure with 2mm thick top

Please have a look at the document CIOKS 10 - Professional range features for more detailed explanation of some of the above features.

NEW!!!

Mounting of CIOKS AC10 power supply underneath Pedaltrain is a step-by-step do it yourself guide on how to attach the AC10 power supply underneath a Pedaltrain pedal board.

The older document CIOKS 10 - Pedal Train attachment shows how to mount the similar size DC10 power supply on top of a Pedaltrain pedal board.

Specifications:

Outlet 1-2: 9V DC / 100mA each

Outlet 3-4: 9 or 12V DC / 200mA each

Outlet 5-6: 9 and 12 or 15V DC / 600mA*

Outlet 7-8: 9 or 12V AC / 800mA*

Outlet 9-10: 9, 12 or 16V AC / 800mA

* only one of these two sections can be used

Size: 158x98x35mm (excl. detachable rubber feet)

Weight: 1,1kg

Warranty period: 5 years worldwide

Order number:

AC10 CIOKS AC10 - Professional power supply for effect pedals with 10 outlets

Flex cables included with CIOKS AC10

- 3 x 1030
- 2 x 1050
- 1 x 1050-I
- 2 x 1080
- 1 x 2050
- 2 x 4050
- 1 x 5050
- 1 x 6050
- 1 x 1035
- 1 x 1022
- 1 x 2200
- 1 x 7050

Total of 16 Flex cables.